

A high-performance kitchen can be aesthetically pleasing, and your Tulip Cooking induction system offers the freedom to create a cooking layout that suits your unique space and style.

Your induction HOBS are **MODULAR** meaning there is no *STANDARD* design pattern or constrictions.

When placing your burner *HOBS* we recommend a minimum of 2.75" between each unit and the back wall.

To explore potential layout options, we recommend cutting craft paper or cardboard to the sizes required. This provides a visual guide prior to cutting countertops.

The TOUCH PAD can be placed up to 27" of the POWER BOX and can be positioned in a number of locations such as a return wall, above a drawer or in the backsplash.

**Request** the fabricator smooths cutouts for cleanest finished installation.

Tulip Cooking HOBS require 220V / 30AMP service. It is important that power remains at 210V or above when all HOBS are in use for proper function. \*IMPORTANT REMINDER, do NOT wire the NEUTRAL wire\*

Programming demo can be found at:

https://www.youtube.com/watch?v=ifU7UtlekbY or search Tulip Cooking on YouTube.

**Please remember** it is important to test the unit prior to application of silicone adhesion for final installation placement.

We recommend waterproof silicone \*not included\* in either clear or black.

*Induction cookware* is *required* when using your new cooktop. To confirm your cookware is induction-ready, simply place a magnet on the bottom of the cookware to make sure it adheres.